Combo CAT6 LCD Console Drawers

Optimize rack space. Maximize rack monitoring

CAT6 KVM Dongle-USB&VGA (DGU)

DVI changer

HDMI changer

DP changer

Features

- Support combo interface, VGA-USB & VGA-PS/2.
- Additional one USB Local console to add local KB/Mouse & VGA.
- Up to 40 meters between Servers to KVM.
- Durable 104-key keyboard and touch pad.
- Quick and simple installation.
- Self-locking and auto release rails for ultra convenience.
- Port selection via push buttons or On-Screen-Display (OSD).
- Dedicated daisy chain port to expand up to 256 servers.

Rear of KVM-1708/1908ASL-M2/ULC



Rear of KVM-1716/1916ASL-M2/ULC



Rear of KVM-1732/1932ASL-M2/ULC

Part No.		KVM-1708ASL-M2/ULC	KVM-1716ASL-M2/ULC	KVM-1732ASL-M2/ULC	KVM-1908ASL-M2/ULC	KVM-1916ASL-M2/ULC	KVM-1932ASL-M2/ULC
Direct no. of Computers		8	16	32	8	16	32
Maximum no. of Computers		232(Daisy Chain)	240(Daisy chain)	256(Daisy chain)	232(Daisy Chain)	240(Daisy chain)	256(Daisy chain)
LCD	Size	17”			19”		
	Backlight	LED			LED		
	Resolution	1280*1024			1280*1024		
	Max. color	16.7M			16.7M		
	Luminance	250cd/m2			250cd/m2		
	View Angel (H/V)	176 / 170			170 / 160		
	Contrast Ratio	1000 : 1			1000 : 1		
Port Selection		Push Button, OSD or Hotkey					
USB Local console		Yes , USB x2 for KB/ Mouse , VGA x1					
Max. Computer Distance		40 meters (Servers to KVM)					
KB/Mouse Emulation		USB & PS2					
Rack Depth		500mm to 1100mm (rack cabinet front rails to rear rails)					
Power		100-240V AC 50/60Hz via IEC Type power cord					
Environment		Operation temp: 0 to 50℃ Storage temp: -20 to 60℃ Humidity: 10% - 90%, non-condensing Shock: 10G acceleration (11ms duration) Vibration: 17 to 500Hz 1G PTP					
Physical Dimensions / Net Weights		448x42x580mm (WxHxD) / 12.0KG			448x42x580mm (WxHxD) / 12.5KG		
Packing Dimensions / Gross weights		715x140x780mm (WxHxD) / 18.0KG			715x140x780mm (WxHxD) / 18.5KG		
Accessory							
1.8meter IEC Type Power Cord							
Option Relate Item							
DGU	CAT6 KVM Dongle-USB&VGA			DVI changer	DVI-to-VGA changer		
DP changer	DisplayPort-to-VGA changer			HDMI changer	HDMI-to-VGA changer		

SAIS - Sacasa Industries & Systèmes
8 rue André Marie Ampère
28500 Vernouillet - France
09 70 440 600 - (+ 33) 970 440 600
https://clavier-ecran-rackable.fr
contact@sacasa.info